

elipson® | A680

6 CHANNEL - POWER AMPLIFIER



**High Audio performances with large power,
elegant and perfect versatility**

6 channel – 3 in stereo (Total power of 480 W @ 4 Ohms) - 3 Zones
- 2 Bus inputs - 2 Bus outputs to connect more A680 multi-channel
amplifiers - Perfect flexibility for audio signal input : Switch for
common audio signal (Bus) or individual stereo channel (line) for
each zone - 6 Individual adjustment for voltage input -Trigger
mode / auto mode / automatic Standby mode - Stereo / Bridge
mode (up to 3 x 150 W @ 8 Ohms)

Type	Multi-zones power amplifier
Channel	6 channel, 3 zones
Power output	80 watts / ch @ 4 Ohms
Bridged power output	150 watts / ch @ 8 Ohms
Total harmonic distortion	<1% 1 kHz / 80 W / 4 Ohms
Channel separation	> 65 dB / 1 kHz 4 Ohms Zone-Zone
Signal to noise	> 90 dB (A weighted Ref : 19 V)
Frequency range	20 Hz - 20 kHz (+/- 3 dB)
Trigger	12V IN & OUT
Damping Factor	> 55 (1 kHz)
Input impedance	> 20 k Ohms
Voltage input	AC 100 - 120 V 60 Hz / AC 220 - 240 V 50 Hz Auto Switching
Safety	CE, CB, NRT, FCC, CE-EMC, ERP
Dimensions	W430 x H88* x D335 mm
Weight	9,5 kg

* without feet



Supplied with mounting brackets for Audio Video Racks
Thickness: 2U

www.elipson.com

Update : 2020/06/17 - Specifications could be changed without notice.