

Built-in 2 x 90 watts (PEAK) amplifier  
HDMI 2 in 1 out  
1 x Minijack input  
Bluetooth input (re-nameable and pin can be set)  
Remote control included  
RS-232  
ARC HDMI Input (allows display to control volume)



Need to punch a hole in the back wall? The SB-1900P soundbar outputs truly impressive sound! The chassis has a matt black finish that enhances any audio-visual installation in meeting rooms, boardrooms, and conference rooms.

### **Rename Bluetooth**

Set any Bluetooth name and Pin. Use PC software to load an image file onto a USB stick. Insert into the soundbar and boot up.

### **Multiple HDMI**

Two HDMI inputs and an HDMI output make connecting to other devices easy.

### **ARC HDMI**

If a display is connected to the ARC input on the soundbar, the display remote control will control the soundbar volume.

### **Analogue Input**

A stereo line-level Minijack input handles normal analogue sources.

### **RS-232 Control**

For professional integration it features RS-232 control via the USB port.

### **Auto Standby**

Choose to use the standard auto standby setting to conserve power, or hold down VOL+ to disable auto-standby.

### **Hanging Brackets**

A set of brackets are included which hang the soundbar under the flat panel. The speaker also comes with rubber feet if you need to place on a shelf, and wall-hanging lugs.

### **Power Cycling**

If mains power is turned off and on, the SB-1900P will automatically come back on resuming the previous settings.

### **Remote Control**

A remote control is included.

## SPECIFICATIONS

**PRODUCT DIMENSIONS**

800 x 90 x 62 mm (width x depth x height)

**PACKAGED DIMENSIONS**

1055 x 155 x 105 mm

**PRODUCT WEIGHT**

2.1 kg

**PACKAGED WEIGHT**

3.6 kg

**CONSTRUCTION MATERIAL**

ABS Plastic

**COLOUR**

Black

**AMPLIFIER OUTPUT**

2 x 90 watts (PEAK) / 2 x 50w watts (RMS)

**DRIVERS**

4

**DRIVER IMPEDANCE**

4 Ohms

**INPUT 1**

Aux in (3.5mm) Input Sensitivity: 700mV

**INPUT 2**

HDMI(2 in 1 out)

**TOTAL HARMONIC DISTORTION**

1% (1kHz, 1W)

**USB-A**

for renaming Bluetooth and RS-232 control

**SPEAKER IMPEDANCE**

8 ohms

**SENSITIVITY**

91 dB (1w/1m)

**FREQUENCY RESPONSE**

(-3dB) 70Hz-20kHz

**POWER CONSUMPTION**

30w (<0.5W standby)

**BLUETOOTH**

V4.2

**MAXIMUM POWER TRANSMITTED**

<5 dBm

**FREQUENCY BANDS**

2402 - 2480 MHz

**POWER INPUT**

DC 20V/3A

**REMOTE CONTROL**

Distance: 6 m Angle: 30° Battery Type: CR 2025

**ACCESSORIES INCLUDED**

1 x Remote Control 2 x L shaped universal mounting strips – to hang soundbar beneath flat panel 1 x USB-A to 9-pin serial adaptor cable, Black 4 x 1.5 m Figure 8 power cable (right-angle plug: UK/EU/US, normal plug: AU), Black

**POWER SUPPLY**

External 100-240v 50/60Hz AC Power Supply – 21 volt / 3 amp. DC tail length: 1.2 m. Transformer dimensions: 128.9 x 51.3 x 34.8 mm, Pin dimensions: Length: 10mm, diameter 6.5mm

**WARRANTY**

Lifetime return-to-base

**COMPLIANCE**

RoHS, WEEE, CE/EMC, FCC, IEC, RCM-POC, RCM-SDOC, REACH, UKCA

**SPARE REMOTE**

SB-1900P RC [EU SAP: 4873590/ US SAP: 13445517]