

TECHNICAL SPECIFICATIONS



LIVE RADIO

LIVE RADIO – a modern music player with integrated Internet radio player, Media player, FM radio tuner and USB flash reader.

Device is connected to LAN network over Wi-Fi or cable interface. Main functions can be controlled with IR remote control. RDS and ID3 support. This device is engineered to provide online music setups, with surprising capabilities.

	LIVE RADIO
Power supply	~ 230 V / 50 Hz
Power consumption	20 VA
Music sources	Internet radio FM radio Media player USB flash
Inputs	75Ω unbalanced FM antenna terminal 2,4 GHz SMA terminal for Wi-Fi antenna RJ45 (Ethernet) cable terminal
Outputs	Stereo RCA Optical output S/PDIF
Max output level	+2 dBu
Internet radio service provider	Frontier Silicon
Radios stations accessibility	up to 1500 Internet radio stations
Internet radio portal	www.wifiradio-frontier.com
Internet radio platform	Jupiter 6.2
Controls	IR remote control
FM frequency range	87,5 – 108 MHz
FM preset stations	10
Internet radio preset station	10
Media player	Supports compressed audio formats
Weight	3,8 kg
Dimensions	482 mm × 44 mm × 305 mm, 1U 19"