

Confidea PS G4

71.98.0028

Power injector for Confidea WAP G4



Description

The Confidea PS G4 is a PoE injector to power the Confidea WAP G4 access point.

The adapter has two RJ45 connectors. One that connects to a switch or PC, the other connector adding power to the access point.

The adapter comes with interchangeable AC clips.

Specifications

Mechanical

Color	Black
Size adapter (W x H x D)	80 x 33 x 45 mm 3.15 x 1.29 x 1.77 in
Size packed (W x H x D)	150 x 48 x 105 mm 5.90 x 1.90 x 4.13 in
Weight adapter	95 g 3.35 oz
Weight packed	204 g 7.2 oz

Electrical

Standard	IEEE802.af compliant
DC Output voltage	56 VDC
Output power	15.4 W
AC Input voltage	100 to 240 VAC
AC input current	0.8 A (RMS) for 115 VAC 0.5 A (RMS) for 230 VAC
AC inrush current	15 A (RMS) for 115 VAC 20 A (RMS) for 230 VAC
AC input frequency	47 - 63 Hz

Environment

Operating temperature	0 – 40°C
Storage and transport temperature	-25 – 65°C
Humidity	<90%, >5%